

INSTRUCTION MANUAL


INSTALLATION INSTRUCTIONS

Clearance from Combustible Materials and Insulation:

DANGER — RISK OF FIRE

Shall not be installed in domestic premises.

Dimension	Min. Clearance Distance
SCB - Top clearance to combustible building element	60mm
MIC – Top clearance to bulk thermal insulation	60mm
HCB – Side clearance to combustible building element	60mm
SCI – Side clearance to bulk thermal insulation	60mm
Clearance between luminaire to independent LED driver	0mm




Note: Use only Power Supply provided. Use of non standard power supply will void warranty.

Warning: This luminaire is not suitable for installation in locations where thermal insulation is present, or may reasonably be expected to be installed in the future, or where there is a likelihood of other combustible material, e.g. leaves or vermin debris, etc. collecting on or around the luminaire. It is not suitable for domestic installations or installation in residential areas of non-domestic installations (residential institutions, hotels, boarding houses, hospitals, accommodation houses, motels, hostels and the like).

If the external exible cable or cord of this luminaire is damaged, it shall be exclusively replaced by the manufacturer or his service agent or a similar qualified person in order to avoid a hazard.

1. This product should only be installed by a licenced electrician in compliance with AS/NZS3000 (current edition) or other regulations that may be relevant to the situation.
2. Ensure desired location is suitable and clear of all obstructions
3. Cut hole with a suitable tool (refer to the table below)
4. Install a suitable standard three pin socket (240V 10A) adjacent to the mounting point.
5. Note: Downlights have a 1.2m flex and plug provided
6. Plug downlight into three pin socket.
7. Hold back the spring clips and insert downlight into opening.
8. Release clips and centre in the opening.
9. Energise and Test.

Maxi Series	Cutout Min (mm)	Frame Diameter (mm)
M6	150-160	165
M7	165-185	193
M8	210-240	245



Warning:
Risk of overheating or fire if the clearance distances are compromised.

Reminder: AS/NZS3000:2007 Amendment 2, Clause 4.5.2.3.2. Where recessed luminaires are installed in an accessible roof space, a permanent and legible warning sign shall be installed in the roof space adjacent to the access panel, in a position that is visible to a person

SEVEN YEAR WARRANTY AGAINST DEFECTS

WARRANTY

Lumex Lighting (Australia Only)

With your new Lumex installation comes the quality assurance provided by the seven (7) year or 35,000 operational hour Warranty (the "Warranty")

The warranty is offered to you by Verbatim Australia Pty Ltd. ("Verbatim") of Unit 6, 450 Princes Highway, Noble Park, VIC 3174

Phone contact: +61 (03) 9790 8999

Subject to the terms of this document, Verbatim warrants to the owner of the Installation that Verbatim will repair or replace, without charge Lighting product (the "Product") if the Product fails due to any manufacturing defect during the first seven (7) years or 35,000 hours of operation following initial installation.

This Warranty applies from the date of invoice for a period of seven (7) years or 35,000 hours of operation thereafter subject to the conditions set in this Warranty.

A. Definitions

In this warranty:

- **Australian Consumer Law** means the Australian consumer law set out in Schedule 2 to the Competition and Consumer Act 2010.
- **Goods** mean the product or equipment that was purchased in Australia.
- **Manufacturer, We or us** means Verbatim Australia Pty Ltd. ABN 39 005 706 374
- **Supplier** means the authorized distributor or the licensed electrical contractor that sold you the Goods.
- **You** means you, the original end-user purchaser of the Goods.

B. Warranty Period and Details

This product is covered by a seven (7) year or 35,000 hours of operation installed warranty against manufacturing faults and defects, provided that:

- The product is properly installed, and installation is consistent with the manufacturer's instructions, and is installed by suitably trained and qualified installer.
- The product is not subjected to any unauthorized modifications.
- The product is only used for the purpose of illumination, in line with its designated purpose or the designated purpose of a luminaire of its general type.
- The product use is in normal conditions and not exceeding a total of 35,000 hours over the warranty period.
- Any faults or defects attributable to the misuse, abuse, accident or non-observance of the manufacturer's instructions on the part of the user are specifically excluded.
- Where a battery product is installed, the warranty period covers 12 months.
- Where a SmartSense™ product is installed, the warranty period covers five (5) years for the sensor technology only.
- Where a third party component is installed within, or as part of, a Lumex fitting, the warranty period is as dictated by the Original Equipment Manufacturer of the third party component.

This Warranty DOES NOT COVER:

- Damage caused by acts of God, or other incidents / occurrences beyond the control of Verbatim, including without limitation, fire, theft, storms, floods.
- Damage caused by water or other forms of moisture being absorbed by the LED light fitting.
- Damage caused by chemical impact or other abuse including environmental factors, improper cleaning solutions, damage from leaving substances such as bleach on the product.
- Damage or problems caused by the use of an accessory, component or equipment not supplied by Verbatim.

C. Extent of the Warranty

Verbatim do not cover freight charges (including insurance) or travelling cost for repairs performed outside the area normally serviced by Verbatim or an authorised repair agent.

- Goods that prove defective within the Warranty Period by reason of improper workmanship or faulty material, wewmay, at our own discretion, either repair or replace the Goods without charge.
- This warranty does not cover any cost related to removal, or reinstallation of the replaced or repaired item. Any parts of the Goods replaced during repairs or any product replaced remain the property of Verbatim.
- In the event of the Goods being replaced during the Warranty Period, the warranty on the replacement Goods will expire on the same date as the Warranty Period of the original Goods they are replacing.

D. Applicable Date/Commencement of Warranty

This warranty commences from the date of purchase from the point of purchase from Verbatim. The details of the point of purchase, as well as all contact information for warranty claims and queries, are detailed below:

Contact: Verbatim Australia Pty Ltd.

Address Unit 6, 450 Princes Highway, Noble Park, VIC 3174
Phone +61 (03) 9790 8999
Fax +61 (03) 9790 8911
Email lighting.orders@verbatim.com.au

E. Claim Process

The customer claim process is as follows:

1. The customer can lodge a claim through the wholesaler from where goods were purchased.
2. The wholesaler/customer must complete the online Warranty Claim Request via the lumexlighting.com.au website.
3. If accepted as a valid claim within the terms as described in this document, Lumex will provide an equivalent replacement product.
4. If goods are to be returned, Lumex will arrange the pickup and return of faulty goods to our warehouse through the wholesaler for further investigation.
5. If the claim is rejected, the customer will be provided with a full explanation and if requested the goods will be returned.

IMPORTANT

Our goods come with guarantees that cannot be excluded under the Australian Consumer Law. You are entitled to a replacement or refund for a major failure and for compensation for any other reasonably foreseeable loss or damage. You are also entitled to have the goods repaired or replaced if the goods fail to be of acceptable quality and the failure does not amount to a major failure.

CUSTOMER SERVICE

+61 (03) 9790 8999

verbatimlighting.com.au